



Dialog 4425 IP Vision

IP Telephone for MX-ONE™
and MD110

Quick Reference Guide

This Quick Reference Guide includes short descriptions on how to use the basic features. To learn more about all available functions and features, please see the related User Guide.

Log on / Log off

Log on: **Own ext. No. Log on**
(If password is requested:
Password **Log on**)
Your telephone might require a network authentication to gain access to the network. In this case you must enter a valid user identity and password (contact your system administrator).

Log off: **Log off Yes**

Answer Calls

Answer:

Handsfree: **Press flashing Line key**

On another extension
(Call pick-up): **Call ringing ext. CallPickUp**

End call: or

Make Calls

Internal calls: **Ext. No.**

External calls: **External line code and No.**

Handsfree: **Dial No.**

Individual external line:

0 **Individual external line No. #**
External line code and No.

Common Speed
Dialing number: **Dial Speed Dialing No.**

Dial by a function key:
Press the preprogrammed key, e.g. Head office

Dial by Contacts
(Phone book): **Press and hold the key with the corresponding letter (Press again for more options)** or **Call**

The complete User Guide is available in electronic format on the Enterprise Telephone Toolbox CD and on: <http://www.aastra.com>

Redial calls from the Call List: or **n Missed** or **Call**

Last External Number Redial: *** * ***
Finland, Sweden: *** * 0**

Inquiry

Ongoing conversation: **Inquiry** **Call 3rd party**

Refer back: **Line 1** or **Inquiry**

Return to first call and finish inquiry: **Line 1**

Transfer

Ongoing conversation: **Conf/Transf** **Call 3rd party**
Transfer (Before or after answer)

Conference

Ongoing conversation: **Conf/Transf** **Call 3rd party**
Conference (After answer)

Callback

Activate: **Callback**
Cancel single
Callback: **# 3 7 *** **Ext. No. #**

Cancel all
Callbacks: **# 3 7 #**

Call Waiting

Activate: **CallWaiting** (At busy tone) **Wait on line**

Intrusion

Activate: **Intrusion** (At busy tone) **Wait on line**

Handsfree

Activate:

Back to handset:

On hook:

Off hook:

Mute

Switch off microphone:

Hold

Individual: **Line**

Resume call: **Line**

Internal Follow-me

Order from your own extension: **Absence** or **Select**
New ext. No. OK

Cancel: **Absence** or **Select**
Deactivate

Redirect from answering position: **Absence** or **Select**
Own ext. No. * New ext. No. OK

Cancel from answering position: **# 2 1 *** **Own ext. No. #**
U.K.: **# 2 ***

External Follow-me

Order: **Absence** or **Select**
External line code and No. OK

Cancel: **Absence** or **Select**
Deactivate

Personal Number

Activate or change profile from own extension: **Absence** **Select** **(1 - 5) OK**

Cancel: **Absence** **Select** **No Profile**

Programming of Function Keys

Program or change a feature: (Two times) **Select**
Press selected function key
No. or code Save Exit or

Voice Mail¹

Enter your mailbox: **Dial voice mail No. and follow recorded instructions.**

New message received: **Message**
Follow recorded instructions.

Account Code¹

New external call: *** 6 1 *** **Account code #**
External line code and No.
Finland and Norway: *** 7 1 ***

Ongoing external call: **Line * 6 1 *** **Account code # Line**
Finland and Norway: *** 7 1 ***

Absence Information¹

Order: **Absence** or **Select**
 or **Select**
Date/Time (If required) OK

Cancel: **Absence** or **Select**
Select

Group Call-pick-up

Answer: *** 8 #**
Finland, Sweden: *** 0 #**

Display Language

Change display language: (Two times) or **Select**
Select or **Select**
Exit or

Silent Ringing

Switch off ring signal:

General Deactivation

Cancel all activated features: **# 0 0 1 #**

Explanations

ext. Extension
No. Number
n Number of missed calls
1 Feature may be optional